



mTS011

LUG MOUNT TEMPERATURE SENSOR



- Tin plated copper mounting lug
- 3/8" (M10), 1/2" (M12) and 1/4" (M6) mounting lug sizes available
- 6'6" (2m) of durable UL 2517 TPE cable with UV protection
- Intrinsically Safe when used with the mBC083 Bus Converter
- Each sensor has a unique permanent digital address
- RJ11 modular jack for easy connection to CMC Field Interconnect Box (FIB)
- No calibration required

The mTS011 is a single-wire temperature sensor in a rugged tin plated copper lug for use in harsh environments. The sensor's recommended operating range is from -40°F to +225°F (-40°C to +107°C) and it is rated as Intrinsically Safe when used with the mBC083 Bus Converter.

The temperature sensor uses a single-wire data communications bus. Up to 32 sensors can be connected in parallel to a single Bus Converter.

The sensor bus has a fully specified cabling system complete with terminal assemblies and uses low cost CAT5/6 cabling and punch down blocks for easy termination. Each sensor has a unique serial number identifying it to the Bus Converter. No sensor calibration is required.

Typical applications include temperature sensing on bearings, motors and other general industrial equipment applications.



mTS011

LUG MOUNT TEMPERATURE SENSOR

SPECIFICATIONS	DESCRIPTION	CHARACTERISTIC
IS SENSOR BUS	Voltage	5 VDC
	Current	1.5 mA maximum
	Communications	Single-Wire Bus
ENVIRONMENT	Recommended Operating Range	-40°F to +225°F (-40°C to +107°C)
	Absolute Maximum Range	-65°F to +255°F (-54°C to +124°C)
	Relative Humidity	0 to 100% sensor end
DIMENSIONS	Length	2.5" (64mm)
	Width	0.6" (15mm)
	Height	0.5" (12mm)
	Mounting Hole -3/8 version	0.406" (10.3mm) for 3/8" (M10) bolt
	Mounting Hole -1/2 version	0.562" (14.2mm) for 1/2" (M12) bolt
	Mounting Hole -1/4 version	0.281" (7.1mm) for 1/4" (M6) bolt
Cable Length	6'6" (2m)	

mTS011-3/8 Single Lug Mount Temperature Sensor 3/8" (M10) mount

mTS011-1/2 Single Lug Mount Temperature Sensor 1/2" (M12) mount

mTS011-1/4 Single Lug Mount Temperature Sensor 1/4" (M6) mount